

# Heat Dissipation Prediction of the M359-1-0 UPS

The Heat dissipation of the M359-1-0 can be estimated, as a function of the load (output power) and the Battery Charge Level (that affects the consumption of the Charger) by using Equation 1 below.

$$P_{diss} = (P_{out} + P_{chg}) \times (1 - Eff) / Eff + 50W \quad (\text{Eq. 1})$$

**P<sub>diss</sub>** is the M359 power dissipation (in the form of heat)

**P<sub>out</sub>** is the output power into the load.

**P<sub>chg</sub>** is the charger's consumption.

When the **Battery Charge Level (BCL)** is less than 50% P<sub>chg</sub> is **250W**.

For **BCL** between 50% to 100% the Charger's consumption gradually drops to zero and can be estimated by using linear extrapolation:

$$P_{chg} = 250 \times (100 - BCL) / 50 \quad (\text{Eq. 2})$$

**Eff** is the efficiency of the UPS double conversion. It is load dependent and is given in Table 1 below:

**Table 1: Conversion Efficiency**

Load	Efficiency (Eff)
500W	0.84
700W	0.86
1,000W	0.88
1,500W	0.86
1,800W	0.84
2,000W	0.83

Use linear extrapolation between brackets.

**The 50W** is the housekeeping power and the cooling fan consumption.

## Examples:

1. **Operating Conditions: Load = 1KW, Battery Charge Level is 30%.**

*Using Eq. 1 above and Eff of 0.88 (from Table 1):*

$$P_{diss} = (1,000 + 250) \times (1 - 0.88) / 0.88 + 50W = \underline{220W}$$

*(Since the Battery Charge Level is lower than 50%, the charger's consumption is taken as 250W).*

2. Operating Conditions: Load = 1KW, Battery is fully Charged.

$$P_{diss} = 1,000 \times (1 - 0.88) / 0.88 + 50W = \underline{186W}$$

3. Operating Conditions: Load = 2KW, Battery Charge Level is 30%.

$$P_{diss} = (2,000 + 250) \times (1 - 0.83) / 0.83 + 50W = \underline{511W}$$

4. Operating Conditions: Load = 2KW, Battery Charge Level is 70%.

$$P_{diss} = (2,000 + 150) \times (1 - 0.83) / 0.83 + 50W = \underline{490W}$$

*Since the Battery Charge Level (70%) is above 50%, the Charger's consumption (Pchg) is estimated by using linear extrapolation between 50% to 100%:*

$$P_{chg} = 250 \times (100 - 70) / 50 = 150W$$

5. Operating Conditions: Load = 1.8KW, Battery is fully Charged.

$$P_{diss} = 1,800 \times (1 - 0.84) / 0.84 + 50W = \underline{393W}$$

6. Operating Conditions: Load = 1.65KW, Battery is empty.

*The Efficiency at 1,650W is calculated as the average between the efficiencies at 1,500W (0.86) and 1,800W (0.84) therefore:*

$$P_{diss} = (1,650 + 250) \times (1 - 0.85) / 0.85 + 50W = \underline{385W}$$